

AVer





# AVer VB350

4K Dual Lens PTZ Video Bar with a Hybrid 18X Zoom for Medium to Large Rooms

# **Product Specifications**

# Camera

- $\cdot$  4K dual-lens technology delivers a wide 113° field of view (FOV) with 18X zoom
- 4K 3X varifocal lens: FOV (D/H/V) 92°/81°/50° - 4K fixed lens: FOV (D/H/V) 113°/105°/71°
- · Sony 4K sensor: ultra-crystal-clear image in any lighting
- Frame rate: (16:9) 1280 x 720 at 60, 30, 15fps; 4K, 3264 x 1836, 2560 x
   1440, 1920 x 1080, 1600 x 900, 960 x 540, 848 x 480, 800 x 448, 640 x
   360 at 30, 15fps; (4:3) 1280 x 960, 800 x 600, 640 x 480 at 30, 15fps
- Adjustable audio fence: Freedom to define wide/ medium/ narrow view fence
   SmartFrame & SmartSpeaker. Automatic tracking and FOV adjustment
- to fit all participants and focus on the speaker
- $\cdot$  Presentation mode: Voice-triggered tracking on both defined areas and speakers
- · Smart gallery\* function enhances visibility
- · Gesture control for intuitive camera control
- · WDR, white balance and more image settings via PTZApp 2
- · Minimum focus distance: 100 cm
- People counting API: Enterprises and third-party software providers can obtain people-counting and meeting-interval data tor better understand meeting space usage
- \* Requires running PTZApp 2 on a PC

#### **Motorized Pan and Tilt Movement**

- · Pan: Total horizontal viewing area 165°
- · Tilt: Total vertical viewing area 101°
- · 10 camera presets

#### Audio

- · 14-element beamforming microphone array
- 10 meters pickup range\*
- · Volume up to 96 dB SPL at 1/2 m
- Echo cancellation
- Al noise suppression

\* The recommended working distance for AI functionality is within 5 meters.

### HDMI

· One cable solution: Built-in USB 3.1	I (Gen 1) to HDMI adapter
--	---------------------------

- · 4K HDMI output to TV\*
- \* Windows® 7 and MAC OS: Need to install HDMI adapter driver

#### Connectivity

•	2V/5A power adapter

- $\cdot$  Mini DIN 6 for RS-232 connection
- $\cdot$  USB 3.1 type B port, backward compatible with USB 2.0
- · HDMI out connection (USB to HDMI adapter)
- · Phone-in (3.5 mm audio Jack)/speaker-out for HA system\*
- · RJ45 ports x2: one for Ethernet, one for audio expansion speakerphone/ microphone
- USB 2.0 type A x3: Wireless connection\*\*, USB to support IFP USB touch back, and expansion port

\* Need to set up via PTZApp 2 and purchase an audio-out converter from AVer \*\* Optional wireless dongle needed to connect with mobile phone

#### Video Format

- · YUV, YUY2, M-JPEG
- Network video compression formats: H.264
- · Network protocols: RTSP, RTMP

#### USB

· 3.1 Gen 1, backward compatible with USB 2.0	
· UVC 1.1 (USB Video), UAC 1.0 (USB Audio)	

#### Control

· IR remote control
<ul> <li>WebUI: IP access via Chrome browser (Chrome 76.x or later; Internet Explorer not supported)</li> </ul>
· VISCA/pelco P/pelco D via RS-232/VISCA over IP
· UVC/UAC plug-and-play
· PTZApp 2

#### Mount and Security

<ul> <li>Wall-mount bracket (included)</li> </ul>	
· TV VESA mount kit (optional)	

· Kensington security lock

# System Requirements

#### Software:

- · Windows® 7/10/11
- · Mac OS X 14.4 or later
- · Chromebox 3 version 94.0.4606.114 or later

#### Hardware:

- · 3.2 GHz Intel® Core™ i5-4460 processor
- · 4 GB RAM or more
- $\cdot\,$  USB 3.1 port, backward compatible with USB 2.0

# **Power Supply**

· AC 100V-240V, 50/60 Hz	
· Consumption: 12V/4.5A	

#### Free Applications for Meeting Collaboration (Free Apps support on Windows® and Mac® computers)

# EZManager 2: Camera Central Management Software

· Remotely group FW/SW upgrades, control the camera, and manage settings

#### PTZApp 2: Camera setting software

- · View live video/people-counting/meeting-interval information
- Smart Gallery/Preset Link
- $\cdot$  Upgrade firmware automatically or manually
- Control the camera
- $\cdot\,$  Set parameters and adjust the camera image
- · Diagnose operating status

# EZLive: Broadcasting software

· Enjoy multi-camera, annotating, image capturing, and video recording

#### Environmental Data

<ul> <li>Operation temperature: 0 ~ 40°C</li> </ul>	
· Operation humidity: 20% ~ 80%	
· Storage temperature: -20 ~ 60°C	
· Storage humidity: 20% ~ 80%	

#### **Package Contents**

· VB350 unit
· Power adapter & cable
· USB 3.1 type B to type A cable (3 m)
· USB 3.1 type A to type C adapter
· QR code card
· Wall-mount bracket
· Tripod Screws
· Remote control
· Wall-mount drill paper

#### **Optional Accessories**

· Mini DIN 6 to RS-232 adapter
· TV VESA mount
· 10 m/20 m expansion microphone
· 10 m/20 m expansion speakerphone
· 5 m USB 2.0 type B to type A cable
· Wireless dongle (for connecting with mobile phone)
· Audio-out converter (TRS female to TRRS male)

#### Dimensions

<ul> <li>Package dimensions: 872 million</li> </ul>	า (L) x 197	mm (W) x	260 mm (H)
---	-------------	----------	------------

- · Package weight: 7.4 kg
- · Camera: 791 mm (L) x 128 mm (W) x 126 mm (H)/3.3 kg
- $\cdot$  Remote control: 150 mm (L) x 42 mm (W) x 19 mm (H)/50 g

#### Warranty\*

# · Accessories: 1 year

\*We offer an optional 2-year extended warranty in the European area. Please contact your local agency for details.

#### **Compatible Applications**

Zoom, Microsoft® Teams, Skype for Business, Skype, Google Meet<sup>™</sup>, Intel® Unite<sup>™</sup>, RingCentral, BlueJeans, V-Cube, LiveOn, CyberLink U Meeting<sup>®</sup>, TrueConf, Adobe® Connect, Cisco WebEx®, Fuze, GoToMeeting<sup>™</sup>, Microsoft® Lync<sup>™</sup>, Vidyo, vMix, WebRTC, Wirecast, XSplit, V Cube

\* For 4K UHD support, please check system/hardware requirements with your software

application provider. \*\* Specifications may vary depending on location and are subject to change without

notice.

#### **Product Overview**

# Front



791 mm (L) x 128 mm (W) x 126 mm (H)

Back



Side



1	Phone-in
2	Audio expansion
3	RS-232
4	USB 2.0 type A (wireless dongle)



1	DC 12V
2	LAN
3	USB 3.0 type B (device to PC)
4	HDMI-out (to TV)
5	USB 2.0 type A port

